### **Technical Support**

For Stanford Unified Messaging support, contact the Service Desk at 5-HELP (650-725-4357) for SU or 4-HELP (650-724-4357) for SHC/SCH, or open a ticket at services. stanford.edu..



Cisco Systems logo are registered trademarks or trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries. All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (070SR) Copyright © 2018 Cisco System, Inc. All rights reserved.

Cisco, Cisco Unity, Cisco Systems, and the

For Custom Keypad Mapping 6, Cisco Unity Connection

September 13, 2018 8:47:43





### Connection Phone Menus and Shortcuts

This card lists the most frequently used Cisco Unity Connection menus and shortcut keys for managing messages and user settings by phone.

## **Accessing Connection**

For a Cisco phone at SU, dial 5-7777 or 650-725-7777.

For a Cisco phone at SHC, dial 7-4444 or 650-497-4444.

For a Cisco phone at SCH, dial 8-4444 or 650-498-4444.

For an Avaya or analog phone, or any phone at a residential location, dial 5-8888 or 650-725-8888.

### Main Menu and Shortcuts

#### Kev(s) Action

.10)(0)	7.0
2	Send a message
3	Review old messages
4	Change setup options
41	Change greetings
412	Turn on/off alternate greeting
421	Change message notification
423	Choose full or brief menus
44	Change transfer settings

## **During Message Menu**

While listening to a message, press:

### Key(s) Action

1	Rewind
11	Repeat message
3	Fast-forward
7	Delete
9	Save
*	Pause/Resume

## After Message Menu

After listening to a message, press:

#### Key(s) Action

11	Repeat message
4	Reply
6	Forward message
7	Delete
8	Play message properties
9	Save

# **Entering Recipients**

To change entry mode, press:

#### Key(s) Action

Switch between addressing a message by name and
addressing by extension

# **Selecting Recipients**

To select recipients from a list, press:

## V-1/2\ A-41

Key(s)	Action
0	Help
1	Repeat name
7	Previous name
77	First name in list
9	Next name
99	Last name in list
#	Select name
*	Exit list

## **Send Message Menu**

After addressing and recording, press:

#### Key(s) Action

,(-,	
1	Mark urgent
2	Request return receipt
3	Mark private
4	Request future delivery
5	Review recording
6	Rerecord
7	Add to recording
91	Add a recipient
92	Play all recipients (and delete recipients)
*	Cancel message

Send message